



## Compatible Dimmer List

MEGAMAN® LED PAR16 7W  
LR2307dDG-WFL and LR2307dDG-VWFL*Dimmer List 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Altenburger	EHR600W	220-240	60-600	1	6
Altenburger	Sim2A	220	60-400	1	6
Anam	ASW 3000-1	220-240	60-1000	1	2
Aurora	AU-DSP400	240	60-400	1	6
British General	AT091-BG	200-250	60-500	1	4
Broco	F25AF	220-240	60-500	1	6
Bticino	CW20 802	250	400	1	6
Bticino	DG07074	220-240	40-900	1	6
Bticino	M9350S	220-240	500	1	1
Bticino	L4581	220-230	50-1000	1	6
Busch	2250U	220-240	60-600	1	6
Busch	2210...510	220-240	60-400	1	3
Busch	6524U	230	2-100	1	6
China IDV	IKT02	220	500	1	3
Clipsal	32V 500 series	220-240	500	1	3
Clipsal	S//E32	250	500	1	2
Clipsal	KB31-RD400	220-240	400	1	3
Clipsal	3031V500M/K	250	500	1	6
Clipsal	32E450ULM	220-240	450	1	2
Contactum	P400	216-253	60-400	1	6
Crabtree	CRO-1W400	220-240	10-600	1	6
Crabtree	CPU-2W400	200-240	60-400	1	4
Danlers	DG05014	230	60-400	1	6
Denmans	HDP-400	200-240	60-400	1	6
Deta	DEP-400DT	200-240	35-400	1	6
Deta	DEP-250DT	200-240	35-250	1	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Dimcontrol	CFL-100	230	1000	1	4
Doyle & Tratt Products	7066	220-240	40-250	1	6
Doyle & Tratt Products	P400	220-240	60-400	1	6
Eagltrise	SED300FHS	220-240	60-300	1	6
Elko	400GLI	220-240	40-400	1	6
Era	DG07037	220-240	300	1	6
Fungyip	F2771	220-240	500	1	6
Garieg	DG04043	220-240	200	1	3
GE	37/56	230	40-500	1	6
GET	EN60669	220-240	250	1	6
GET	R25E	200-250	60-250	1	6
Gewiss	GW 20 803	230	300	1	6
Gira	03000	230	20-500	1	6
Hamilton	L400/2	220-240	400	1	6
Home Automation	VID dimr100e	200-250	50-500	1	6
Home Automation	5261	220-240	100-600	1	6
Igoto	DG04041	220-240	200	1	2
IKEA	E0902-DIM	220-240	25-150	1	6
Insta	Gira 1176 00/ 100	230	50-420	1	6
Jin Meung (SK)	DG04047	220-240	630	1	3
Keytop	BP1000	220-240	1000	1	6
Legrand	ADWGL4	220-240	40-400	1	6
Legrand	Mosaic	220-240	60-500	1	6
Legrand	Haut 100-1000VA	250	100-1000	1	6
Legrand	ADW-GL6	230	60-600	1	6
Legrand	BMD 300	100-240	40-300	1	3
Legrand	7354 90	230	40-400	1	6
Leviton	BME04-2L	220	400	1	6
LK	506DA117	230	20-300	1	6
Makel	DG07095	230	450	1	6
Merten	5722	230	60-600	1	6
MK	42804PL	230	40-250	1	6
MK	GX8051	220-240	40-500	1	6
MK	L/N1511	230	60-450	1	4
MK	SX8051	240	40-500	1	2
MK	52471SL	230	60-500	1	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
National	WEG57515	220-240	40-500	1	6
National	WNG6801	220-240	500	1	6
National	WNG575253	220-240	60-600	1	6
Niko	09-013	230	60-300	1	5
Nisko	DG08050	220-240	1000	1	6
Ove	80.33	230	40-400	1	2
Panasonic	WEJ57515	220	40-500	1	6
Pol	CAT 1593M	220-240	500	1	6
Richmond	MP500	230	40-400	1	6
Richmond	GRID700	240	75-700	1	2
Richmond	GRID400CFL	240	400	1	6
Richmond	GRID500	240	40-500	1	6
Schneider	GU6012	220-240	60-400	1	6
Schneider	SD300	220-240	300	1	6
Schneider	C460	220	400	1	1
Schneider	WDE002747	230	9-100	1	6
Sicherung	Grundtyp H1	230	20-500	1	6
Simen	Simen 55	150-250	40-150	1	3
Simon	Simon..813	220-240	40-500	1	6
Simon	75313-39	230	40-500	1	6
Soben	C8M2	200-250	630	1	6
Stsbén	Stsbén 86	220	15-200	1	2
Switchlight	SW-316	220-240	500	1	6
T&J	P2017S	220-240	40-630	1	6
TCL	KGM2	220-240	500	1	6
TCL	LM2	220	630	1	6
Varilight	JQP401W	230	10-400	1	6
Venus	9720	220	40-900	1	6
Viko	215	220-240	600	1	6
Vi-ko	90 30 48	220	600	1	6
Vimar	Plana 14150	230	100-500	1	6
Vivian	D-21102	220-240	1000	1	6
Zano	ZGRID500	230	500	1	6

Remarks: \*The minimum and maximum number of LED lamps compatible depends upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation. Copyright © MEGAMAN® 2013. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice. All other trademarks mentioned are the property of their respective owners.