

SPECIAL LAMPS

CROWN SILVER

Flawless mirror lighting with an aesthetic touch

With a unique silver-plated design and clear light bulb finishing, the LED Crown Silver offers dramatic lighting with an aesthetic touch, making it the perfect solution for decorative applications.

The MEGAMAN® LED Crown Silver delivers non-glare lighting just like an incandescent lamp with silver coating, while greatly reducing electricity and maintenance costs. When these lamps are fitted around a mirror frame or as decorative lighting, the light beam is well controlled and dramatic effects can be easily achieved.

Product Features

- Unique silver-plated design in A60 lamp shape with a silvered crown top and clear light bulb finishing
- Brass-plated design; "gold-looking" coating is available for the A60 shaped lamp
- Best for mirror lighting and decorative lighting
- Capable for linear dimming from 100% to 10%#
- High colour rendering of up to Ra85
- High luminous maintenance: rated lumen maintenance life of 70 (L70) at up to 50,000 hours
- High colour temperature consistency
- Generates much less heat than an incandescent bulb
- Operating temperature: -30°C to +40°C



* Please visit www.megaman.cc/user-guide for a list of compatible dimmers.



SPECIAL LAMPS

CROWN SILVER



220-240V | Line Voltage

Lamp Type	Product Code	Wattage (W)	CRI	Rated Life (hrs)	Diameter (mm)	Length (mm)	Weight (g)	Dimmable	Product Photo	
Smart Series										
Classic P45	LS0303.5d-E14-2800K-230V*	3.5	80	25000	45	84	35	100-10%	1	
Classic P45	LS0303.5d-E14-4000K-230V*	3.5	80	25000	45	84	35	100-10%	1	
Classic A55	LS0406d-E27-2800K-230V*	6	80	25000	55	104	78	100-10%	2	
Classic A55	LS0406d-E27-4000K-230V*	6	80	25000	55	104	78	100-10%	2	
Classic A60	LS0107d-E27-2800K-230V	7	82	30000	60	106	131	100-10%	3	
Classic A60	LS0107d-E27-4000K-230V	7	85	30000	60	106	131	100-10%	3	
Classic A60	LS0107d-Brass-E27-2800K-230V	7	82	30000	60	106	131	100-10%	4	
Classic A60	LS0107d-Brass-E27-4000K-230V	7	85	30000	60	106	131	100-10%	4	

Capable of linear dimming from 100% to 10% when working with most conventional dimmers for incandescent lamps or halogens; please refer to the compatible dimmer list at www.megaman.cc/user-guide for further details.
* Preliminary data