



Compatible Halogen Transformer List

MEGAMAN® LED MR16 7W
ER3207-50H24D and ER3207-50H36D*Halogen Transformer 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Actec	MINI60	230-240	20-60	1	1
Allttx	MT60	230	60	1	1
Anchorn	AET-3502R1	220-240	35-150	1	3
Andawo	MR-128	220	20-50	1	1
Atom	Tiger	230-240	20-60	1	1
Aurora	AU-E60	240	10-60	1	1
Barrow	TED20600209-100310	220	60	1	1
BAW	TREH60C1 6-60w	220	60	1	1
Collingwood	SKY I 60	240	20-60	1	1
Dais	DA-J60	240	20-60	1	1
Dura	DELT12060P	230	20-60	1	1
Dura	DELT12105M	220-240	35-150	1	3
Eico	E60W	220-240	10-60	1	1
ELT	TR 5/23-01-SC	230	50	1	1
EMC	ET105	230	35-105	1	2
Emcolite	EMRED60	240	20-60	1	1
Enlite	EN-SC60	240	20-60	1	1
ERC	TRAEK02	230	20-60	1	1
Eterna	T60VA	240	20-60	1	1
FLC	ET60A	230	3-60	1	1
Generic	TE12/70 CODE SB1240-B	220-240	10-70	1	1
Geni	GT-006	170-240	60	1	1
Gira	Tronic-Trafo 0366 00	230	20-70	1	1
Gira	Tronic-Trafo 0371 00	230-240	20-105	1	2
Gira	Tronic-Trafo 0378 00	230-240	20-105	2	2
Halolite	HA-S105	240	35-105	2	2
Halolite	HA-SE60	240	20-60	1	1
HEP Group	TB60I 230 10-60W	230	10-60	1	1
HEP Group	TE105S 20-105W	230-240	20-105	1	2
HEP Group	TL150S 50-150W	230-240	50-150	1	3
HEP Group	TR70 10-70W	230	10-70	1	1
Horoz	HL317	220	150	1	1
JCC	JC4030(10-60AV)	220-240	10-60	1	1



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Kengo	DET-60S	220-240	10-60	1	1
Kengo	Ket105	230-240	35-105	1	2
Light Division	ET60A	230	20-60	1	1
Lightech	LET 105/240	240	35-105	1	2
Lightech	LET 75/12V	230-240	20-75	1	1
Lightron	ETH-55Eco	240	50	1	1
Lite-Tech	SY1507/W	220-240	20-60	1	1
Lival	Pico Wolf 60	220-240	60	1	1
Lival	Pico Wolf 70	220-240	70	1	1
Loretto	LT60	220-240	20-60	1	1
Lucci	TB60L 240 10-60W	240	10-60	1	1
MP Lamp	T60	220-240	10-60	1	1
Nelson	MICRO 60	230-240	60	1	1
Niko	320-00106	230	20-70	1	1
Niko	320-00121	230	20-70	1	1
Nobile	EN-110D2	230	35-110	1	2
NVC	ET60E	220	20-60	1	1
Onnline	Pico Wolf 70	230-240	70	1	1
Orbit Lighting	LET60B	240	10-60	1	1
Osram	ET-A 60/220-240	220-240	20-60	1	1
Osram	ET-LED 30/220-240	220-240	2-30	1	1
Osram	ET-P 60/220-240	220-240	20-60	1	1
Osram	ET-Parrot 105/240 I	240	35-105	1	2
Osram	ET- Parrot 70/220-240 I	220-240	20-70	1	1
Osram	ET-REDBACK 60VA/230-240	230-240	20-60	1	1
Osram	ET-Z 60/220-240	220	20-60	1	1
Osram	Halotronic HTM 150/230-240	230-240	35-150	1	3
Osram	Halotronic HTM 70/230-240	230-240	20-70	1	1
Osram	IZ-A 50/240	240	50	1	1
Osram	IZ-HALO 50/220-240	220-240	20-50	1	1
Philips	Certaline 60w	230	20-60	1	1
Philips	EHC250 F	220	35-60	1	1
Philips	ET50 220/12V	170-250	40-60	1	1
Philips	ET-E60 220-240	220-240	20-60	1	1
Philips	ET-S 60 220-240	220-240	20-60	1	1
Philips	Primaline 105 230-240	230-240	35-105	1	2
Philips	Primaline 150 230-240	230-240	50-150	1	3
Philips	Primaline 70 230-240	230-240	20-70	1	1
Puma	ET-075P-230-RD	230-240	35-75	1	1
QLT	W60	230	20-60	1	1
Radium	ET-RALOPOWER	230-240	60	1	1



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Reico	RN1613	230-240	100-160	1	3
Releo	MICRO 60 PFS	230-240	10-60	1	1
RIO	RT060CP	220V	60	1	1
Robus	LDT150N	230-240	35-150	1	3
Robus	LT60d	240	20-60	1	1
Robus	RM70DN	220-240	70	1	1
Sector	ALVT60ED	240	20-60	1	1
Self	SET105F-2	230	35-105	1	2
Self	SET70F-2	230	20-70	1	1
Self	SET70R	220-240	20-70	1	1
Sylvania	MINI 60	220-240	20-60	1	1
TAO	SET150-2	230	50-150	1	3
TCI	MW 70 LED	230-240	1-70	1	1
TCI	Pico Wolf 105	230-240	105	1	1
TCI	Pico Wolf 60 V.2	230-240	10-60	1	1
TED	WIN-60SLV	220-240	10-60	1	1
Tridonic	Atco Possum 60VA 89400035	230-240	60	1	1
Tridonic	Atco Speedy TE-0070 C101	230-240	20-70	1	1
Tridonic	Atco TE-0105 S003	230-240	105	1	1
Tridonic	Atco Viper 60VA 22176070	230-240	60	1	1
Tridonic	Speedy TE-0105 C101	230-240	35-105	1	2
Tridonic	Viper 105 22176074	230-240	105	1	2
Tridonic	Viper 60 22176072	230-240	60	1	1
Tridonic	Viper 60VA 22176110	230	60	1	1
Ushio Group	456001	230	0-60	1	1
Voitwell	V3YB-50-B	220	20-50	1	1

*Remarks: The minimum and maximum number of LED lamps compatible depends upon the performance of the halogen transformer, which is subject to the status of the manufacturer's technology. Due to possible variations in country halogen transformer module specifications, please contact your local distributor for a list of compatible halogen transformer before installation.
Copyright © MEGAMAN® 2014. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.